



惠州硕贝德无线科技股份有限公司

Huizhou Speed wireless technology Co.,Ltd

ANTENNA SPECIFICATION

Customer/ Project	R0101		Frequency Band	76GHz~81GHz	
SCT P/N	F-PL-08-0001-001-S0		Version	V1.0	
Date	2024.04.26				
SPEED					
Checked by	RF	Leslie Tan	Designed by	RF	Kai Zhang
	ME	Simon Lin		ME	Ke Zhou
	QC	Zhongzheng Wang	Remark		
Customer					
Date					
Confirmed by	RF				
	ME				
Remark					

www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

Revision record

Date	Revision version	Change Description	Author
2024.4.26	V1.0	Initial release	Kai Zhang

www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

Catalogue

revision history	2
1. Overview	4
2. antenna specification	5
3. antenna passive performance	6
4. antenna structure	11

www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

1 Overview

This document provides specifications for the R0101 waveguide antenna working in the 76-81GHz frequency band.




Figure1 R0101 overview




Figure2 antenna definition layout

www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

2 antenna specification

Antenna type	Injection molding plastic waveguide ANT.
Working Frequency	76GHz~81GHz
Gain	≥15dBi
Return Loss	S11<-15dB@76-81GHz for all ports
Isolation	Rx-Rx, Tx-Tx isolation > 25dB Tx-Rx isolation > 35dB
Ports type	8 ports (4TX+4RX)
polarization	Horizontal
3dB beamwidth	Azimuth >57deg Elevation >9deg
6dB beamwidth	Azimuth >93deg Elevation >13deg
Side lobe level(dB)	<-20dB
Feeding type	Waveguide ports ,Lauch on Package
size(L*W*H)	70.7*61.7*13.4mm
weight	45g
Working temperature	-20 °C to +85 °C
Storage temperature	+20 °C to +25 °C

www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

3 passive performance

3.1 Return Loss

$S_{11} < -15\text{dB}$ @ 76-81GHz (feeding from FR4 PCB)




Figure3 Return loss

3.2 Isolation

$\text{TX-TX, RX-RX} > 26.3\text{dB}$

$\text{TX-RX} > 46.3\text{dB}$





Figure4 Isolation

3.3 Radiation Pattern


www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

RX1 antenna




Curve Info	Gain	1(-75deg)	2(75deg)	3(-30deg)	4(30deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='90deg'	16.0128	8.2426	4.4007	13.9004	14.3407
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='90deg'	15.8440	7.9656	4.4455	13.8707	14.2460
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='90deg'	16.0535	8.0992	4.2247	14.0088	14.3995
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='90deg'	16.3116	8.1636	4.6789	14.2776	14.5539
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='90deg'	16.6920	8.4377	4.9708	14.7505	14.9726
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='90deg'	17.0196	8.7163	4.8492	15.2066	15.4281




Curve Info	Gain	1(-10deg)	2(10deg)	3(-5deg)	4(5deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='0deg'	15.4350	7.2443	7.0018	13.4341	13.3964
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='0deg'	15.2967	7.0823	6.9371	13.3893	13.3360
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='0deg'	15.5420	6.7491	6.7834	13.4890	13.5153
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='0deg'	15.8007	5.8422	6.2030	13.4025	13.5152
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='0deg'	16.1992	4.4690	5.0445	13.3890	13.5431
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='0deg'	16.5953	1.8255	2.8713	13.2513	13.4239

RX2 antenna



Curve Info	Gain	1(-75deg)	2(75deg)	3(-30deg)	4(30deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='90deg'	16.1910	6.0123	4.8671	14.7515	13.5181
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='90deg'	16.0854	6.2313	4.2928	14.6137	13.5333
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='90deg'	16.2063	6.4246	4.4053	14.6882	13.6884
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='90deg'	16.2838	6.4833	4.6020	14.8451	13.9017
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='90deg'	16.5994	6.8474	4.8563	15.1281	14.2573
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='90deg'	16.9795	7.0619	5.2141	15.4785	14.6692




Curve Info	Gain	1(-10deg)	2(10deg)	3(-5deg)	4(5deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='0deg'	15.1556	6.5757	6.8927	13.0896	13.1118
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='0deg'	15.1503	6.6336	6.7243	13.1103	13.1459
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='0deg'	15.4148	6.5687	6.3034	13.2933	13.2590
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='0deg'	15.6440	5.8981	5.3364	13.3409	13.2125
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='0deg'	16.0834	4.7870	3.6715	13.4062	13.1969
dB(RelizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='0deg'	16.4228	2.6140	0.6759	13.2733	12.8638


www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

RX3 antenna




Curve Info	Gain	1(-75deg)	2(75deg)	3(-30deg)	4(30deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=76GHz' Phi='90deg'	16.0958	5.5128	4.3782	13.5949	14.6445
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=77GHz' Phi='90deg'	16.0566	5.3340	4.5963	13.6119	14.6178
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=78GHz' Phi='90deg'	16.1899	5.4201	4.6681	13.7093	14.7202
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=79GHz' Phi='90deg'	16.3982	5.6415	4.8965	14.0063	14.9063
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=80GHz' Phi='90deg'	16.6924	5.8691	5.0677	14.3390	15.1268
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=81GHz' Phi='90deg'	17.0904	6.1790	5.2403	14.7375	15.4208




Curve Info	Gain	1(-10deg)	2(10deg)	3(-5deg)	4(5deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=76GHz' Phi='0deg'	15.0435	6.6391	6.6330	12.9970	12.9990
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=77GHz' Phi='0deg'	15.1746	6.7193	6.8400	13.2021	13.2179
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=78GHz' Phi='0deg'	15.3110	6.3201	6.5821	13.2441	13.2778
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=79GHz' Phi='0deg'	15.6342	5.5587	6.0920	13.2772	13.3950
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=80GHz' Phi='0deg'	15.9635	3.8731	4.9364	13.1038	13.3870
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=81GHz' Phi='0deg'	16.2914	0.8848	2.8680	12.8250	13.1903

RX4 antenna



Curve Info	Gain	1(-75deg)	2(75deg)	3(-30deg)	4(30deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=76GHz' Phi='90deg'	15.8774	4.7483	5.7105	14.3942	13.6167
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=77GHz' Phi='90deg'	15.8275	5.0732	5.6164	14.4802	13.7631
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=78GHz' Phi='90deg'	15.9615	5.2780	5.8078	14.5404	13.8537
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=79GHz' Phi='90deg'	16.1832	5.3867	5.9308	14.7542	14.1392
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=80GHz' Phi='90deg'	16.5198	5.5457	6.1307	15.0788	14.5501
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=81GHz' Phi='90deg'	16.8314	5.7331	6.3515	15.4262	14.9554




Curve Info	Gain	1(-10deg)	2(10deg)	3(-5deg)	4(5deg)
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=76GHz' Phi='0deg'	15.3233	6.9202	6.8319	13.2625	13.2328
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=77GHz' Phi='0deg'	15.3667	6.9173	7.1053	13.3478	13.3998
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=78GHz' Phi='0deg'	15.5250	6.4884	6.9404	13.3971	13.4925
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=79GHz' Phi='0deg'	15.7924	5.6313	6.3831	13.4013	13.5529
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=80GHz' Phi='0deg'	16.1212	3.9825	5.2805	13.2681	13.5385
dB(RelizedGainTotal) Setup1 : Sweep1 Freq=81GHz' Phi='0deg'	16.4901	1.1051	3.2729	12.9933	13.3801


www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

TX1 antenna




Curve Info	Gain	1(-75deg)	2(75deg)	3(-30deg)	4(30deg)
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='90deg'	16.6783	5.3944	3.5835	13.2548	14.0052
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='90deg'	16.6454	4.8960	4.1591	13.2445	13.7890
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='90deg'	16.7070	4.8209	4.4385	13.4452	13.8199
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='90deg'	16.9255	5.3030	4.4670	13.6594	14.0388
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='90deg'	17.2901	5.7829	5.3721	13.9635	14.2396
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='90deg'	17.8772	6.0584	5.6792	14.4633	14.7100




Curve Info	Gain	1(-10deg)	2(10deg)	3(-5deg)	4(5deg)
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='0deg'	16.5085	7.5293	7.7145	14.3211	14.3752
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='0deg'	16.4110	7.9385	7.9506	14.4047	14.4059
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='0deg'	16.5209	7.8445	7.7140	14.4942	14.4542
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='0deg'	16.7378	7.1610	6.9014	14.5219	14.4408
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='0deg'	17.0871	5.9879	5.3075	14.5200	14.3469
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='0deg'	17.6650	3.9939	2.4820	14.5989	14.2730

TX2 antenna



Curve Info	Gain	1(-75deg)	2(75deg)	3(-30deg)	4(30deg)
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='90deg'	16.7083	4.2521	4.6003	13.1050	13.4893
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='90deg'	16.6601	3.8718	4.4779	13.0175	13.3270
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='90deg'	16.7087	3.8880	4.5557	13.0378	13.3108
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='90deg'	17.0091	4.1583	4.9226	13.4127	13.4779
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='90deg'	17.2644	4.6349	5.3440	13.7415	13.7546
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='90deg'	17.7997	5.0131	5.8690	14.3451	14.3049





Curve Info	Gain	1(-10deg)	2(10deg)	3(-5deg)	4(5deg)
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='76GHz' Phi='0deg'	16.5352	6.9538	7.1964	14.1832	14.2955
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='77GHz' Phi='0deg'	16.5276	7.5493	7.7379	14.3348	14.4193
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='78GHz' Phi='0deg'	16.4738	7.5431	7.5218	14.3817	14.3499
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='79GHz' Phi='0deg'	16.7426	7.2625	6.7687	14.5622	14.3786
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='80GHz' Phi='0deg'	17.0144	5.9068	4.9857	14.4296	14.1268
dB(RealizedGainTotal) Setup1 : Sweep1 Freq='81GHz' Phi='0deg'	17.6404	3.7336	2.1278	14.4125	14.0581



www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

TX3 antenna



TX4 antenna



www.speed-hz.com

SPEED has possession of proprietary information provided in this presentation and this proprietary information shall be kept in strict confidence and not disclosed to any person or firm without the prior written consent of SPEED Wireless Technology

4 antenna structure

